




## **MNTBRKT-HL-8-30-SS**

Ruland Sensor Bracket, Thru Hole 8mm, W 30mm, Stainless Steel





## Description

Ruland MNTBRKT-HL-8-30-SS is a mounting bracket with a 8mm thru hole, 30mm bracket width, M8 center tapped hole, and M4 tapped holes in the cross. It is designed to fit with Ruland bracket clamps. MNTBRKT-HL-8-30-SS is made of stainless steel for corrosion resistance and durability in a variety of industrial environments. It is primarily used to mount 8mm sensors in a variety of applications industries including packaging, printing, food processing, and medical. MNTBRKT-HL-8-30-SS is manufactured by Otto Ganter, inventoried by Ruland, and RoHS3 compliant.

## **Product Specifications**

| Thru Hole Diameter B     | 8 mm   | Center Mounting Screw C1 | M8                    |
|--------------------------|--|--------------------------|-----------------------|
| Cross Mounting Screws C2 | M4   | Edge To Center L2        | 24.5 mm               |
| Center To Center LC      | 20 mm  | Edge to Screw L3         | 20.5 mm               |
| Bracket Width W          | 30 mm  | Thickness T              | 2.5 mm                |
| Base Length L1           | 35.5 mm  | Weight (Ibs)             | 0.052900              |
| Material Specification   | 304 Stainless Steel  | Manufacturer             | JW Winco/ Otto Ganter |
| UPC                      | 634529229446   | Country of Origin        | Germany               |
| Tariff Code              | 7609.00.0000   | UNSPC                    | 31162908              |
| Note 1                   | Performance ratings are for guidance only. The user must determine suitability for a particular application.   |                          |                       |
| Prop 65                  | <b>MARNING</b> This product can expose you to the chemical Nickel (metallic), known to the State of California to cause cancer. For more information go to <u>www.P65Warnings.ca.gov</u> . |                          |                       |
|                          |  |                          |                       |